## **Technical data sheet**

0° socket, with earthing pin, triple

**Item number: 6120194** 



Socket with earthing pin, triple  $0^\circ$ , with increased touch protection, with screwless terminals, 2-pin, 16 A, 250 V $^\circ$ , with connection terminals to IEC 60884-1. For installation in Rapid 45 trunking, device installation trunking, service poles, underfloor systems and desk boxes.







Polycarbonate

B.A			 _	_	4_
М	n s	414	м	ы	га

Item number	6120194		
Туре	STD-F0 ROR3		
Description 1	Socket 0°, triple		
Description 2	with earth pin		
Manufacturer	OBO		
Dimension	250V, 10/16A		
Colour	Pure orange; RAL 2004		
Material	Polycarbonate		
Smallest sales unit	1		
Unit of quantity	Piece		
Weight	11.8 kg		
Weight unit	kg/100 pc.		


## **Technical data sheet**

# 0° socket, with earthing pin, triple





# Dimensions Width Height 135 mm 45 mm



#### Technical data

-			
Cover	Central plate		
Closable	no		
Connection type	Screwless terminal		
Number of units	3		
Number of modules (for modular construction)	0		
Number of switchable sockets	0		
Number of poles	2		
Printed label/coding	Without printing		
Version for	Triple 0°		
Surface version	Matt		
Version for	Protective contact pin		
Ejection mechanism	no		
Fastening type	Lock		
Labelling panel	no		
Operating temperature, max.	40 °C		
Operating temperature, min.	-5 °C		
increased touch protection	yes		
Error current protection	no		
For more difficult conditions (according to VDE)	no		
Halogen-free	yes		
Insulated installation	no		
Hinged cover	no		
Coding	no		
Waming light	no		
With on/off switch	no		
With fine-wire fuse	no		
With functional lighting	no		
With orientation lighting	no		
Mounting type	Device installation duct		
Nominal voltage	250 V		
Nominal current	16 A		
Protection rating	Other		
Special power supply	Without special power supply		
Socket version	NF		
Socket angle	0°		

# **Technical data sheet**

0° socket, with earthing pin, triple

**Item number: 6120194** 



Technical data		
	Depth	39 mm
	Transparent	no
	Rotated central insert	no
	Approvals	VDE
;	Surge protection	no